

Miscelatori - Accoppiatori - Partitori da palo

mixers - couplers - mast splitters



83100L

LTEfree™

La vasta gamma di modelli LTEfree consente una grande versatilità nella gestione e nella combinazione dei segnali televisivi e FM. Tutti i miscelatori e gli accoppiatori di segnale sono interamente schermati, provvisti di connessione tipo "F" e realizzati con componenti di alta qualità a garanzia di basse perdite di inserzione e alta selettività. La custodia in plastica antiurto, fornisce la massima protezione dagli agenti atmosferici.

Thanks to the wide range of models it is very easy to manage and combine TV and FM signals. All mixers and signal couplers are completely screened, endowed with F connectors and realized with high quality components to guarantee low insertion loss and high selectivity. The anti-shock plastic case is weatherproof.

miscelatori/mixers

codice code	ingressi inputs n°	bande bands	perdite inserzione insertion loss VHF/UHF dB	uscite outputs n°	Return Loss Return Loss dB
83100L	2	VHF - UHF (K. 21-60)	0,5 / 0,7	1	< -14
83101CE	2	B.V + Trappola di canale - Log B.V + stop channel - Log	3,5 / 4,0	1	< -14
83101AL	2	UHF (K. 21-60) - Log (K. 5-60)	3,5 / 4,0	1	< -14
83102CE	2	VHF - UHF	3,5 / 4,0	2	< -14
83109CE	3	VHF - UHF - UHF	3,5 / 6,0	2	< -14
83110CE	3	VHF - UHF - UHF	0,5 / 4,0	1	< -14
83110L	3	VHF - UHF - UHF	0,5 / 4,0	1	< -14
83120CE	3	VHF - B.IV - B.V	0,5 / 0,7	1	< -14
83120P20	2	UHF (K. 21-60) - K. 63-69	0,5 / 0,7	1	< -14

■ : Limita disturbo LTE

■ : Reduces LTE interference

accoppiatori/couplers

codice code	ingressi inputs n°	bande bands	perdite inserzione insertion loss VHF/UHF dB	uscite outputs n°	Return Loss Return Loss dB
83196CE	2	VHF	0,2 / -	1	< -16
83198CE	2	UHF	- / 0,2	1	< -16
83199CE	4	UHF	- / 0,2	1	< -16

partitori/splitters

codice code	ingressi inputs n°	bande bands	perdite inserzione insertion loss VHF/UHF dB	uscite outputs n°	Return Loss Return Loss dB
83190CE	1	VHF+UHF	3,5 / 4,0	2	< -14
83193CE	1	VHF+UHF	7,0 / 8,0	3 (1cc)	< -14
83194CE	1	VHF+UHF	7,0 / 8,0	4 (1cc)	< -14